

CONSTRUCTION PRODUCTS
**BUCHANAN
SPLICE CAP**

COPPER WIRE ONLY

TO INSTALL: Strip wires approximately 3/4" long. Insert wires thru cap and twist. Insert Buchanan C24 or P24 pres-SURE-tool with latch at "B", Squeeze. Cut wires flush after crimping. INSULATE with BUCHANAN #2014 nylon insulator.

TO REMOVE: Snip cap at both ends of one crimp or squeeze alternately 90° apart between crimps.

UL and CSA listed as "pressure cable connectors" for 5-11 #14, 3-7 #12, 2-5 #10, 2-3 #8 2 #6 stranded; 4-10 #14, 3-6 #12, 2-4 #10, 2 #8 solid. Consult factory for complete list of wire combinations.



IDEAL INDUSTRIES, INC.
Sycamore, IL 60178, U.S.A.
800-435-0705 • www.idealindustries.com
1075106 AW 101B
Made in U.S.A. of US and global components.

CAT. NO. QTY.
2011SB/500



CONSTRUCTION PRODUCTS
**BUCHANAN
SPLICE CAP**

COPPER WIRE ONLY

TO INSTALL: Strip wires approximately 3/4" long. Insert wires thru cap and twist. Insert Buchanan C24 or P24 pres-SURE-tool with latch at "B", Squeeze. Cut wires flush after crimping. INSULATE with BUCHANAN #2014 nylon insulator.

TO REMOVE: Snip cap at both ends of one crimp or squeeze alternately 90° apart between crimps.

UL and CSA listed as "pressure cable connectors" for 5-11 #14, 3-7 #12, 2-5 #10, 2-3 #8 2 #6 stranded; 4-10 #14, 3-6 #12, 2-4 #10, 2 #8 solid. Consult factory for complete list of wire combinations.



IDEAL INDUSTRIES, INC.
Sycamore, IL 60178, U.S.A.
800-435-0705 • www.idealindustries.com
1075106 AW 101B
Made in U.S.A. of US and global components.

CAT. NO. QTY.
2011SB/500

